

Volume Controller with emergency relay HYU-PA-VC001




Key Features

- With override function, firefighting linkage.
- The power of the volume controller is 60W.
- 5 gear volume adjustment.
- Elegant and compact design


Specifications

Model	HYU-PA-VC001
Type	Five Gear Volume Control
Rated power	60W
Override signal	24V DC 10mA
Gear output (Input 1kHz/100V, Load=82Ω, distortion degree <1%)	STEP : 0V (off) STEP1 : 13(±2) V STEP2 : 26(±2) V STEP3 : 51(±2) V STEP4: 100V
Gear Freq. Response (Normal operating conditions (-3DB))	STEP1 : 70Hz ~ 18kHz STEP2 : 70Hz ~ 18kHz STEP3 : 70Hz ~ 18kHz
Input DC24V override signal output (position switch can be placed at any location)	100V (Input 1KHZ/100V, Load=82Ω, distortion<1%)

Dimension



Volume control knob
(Front view)



Dimension